

PULSE OXIMETER FINGERTIP CMS-50DL

BASIC FINGER WITH LCD DISPLAY



FEATURES:

- Intergrated with SPO2 probe and processing display module.
- Light and compact design
- Can be used in Hospital, home, community medical treatment, sports healthcare etc.
- Can Measure SPO2 and Pulse Rate accurately
- SPO2 and Pulse Rate display, Bargraph display
- Battery voltage low indication
- Low power consumption
- Automatic Power off Function

CODE: POX50DL

SPECIFICATIONS:

MODEL:	CMS-50DL
DIMENSIONS:	57MM (L) X 33MM (W) X 32mm (H)
DISPLAY FORMAT:	LED Display
SPO2:	35 – 99% Pulse Ratio – 30~250BPM
RESOLUTION:	1% For SPO2, 1 BPM for Pulse Ratio
ACCURACY:	(2%)70 – 99% Unspecified (<70%) for SPO2, 2BPM OR 2% (select larger) For Pulse Ratio
POWER SUPPLY	Battery Voltage: DC2.6V – 3.6V 1.5V (AAA) size alkaline batteries x 2
CONTINUOUS USE	30 HOURS >
INTERFERENCE RESISTANCE CAPACITY AGAINST AMBIENT LIGHT AND MEASUREMENT PERFORMANCE AT LOW PERFUSION	
QUALITY APPROVAL	CE